


# 12V Programmable 7 Day Timer

Model: TS2000

## CAUTION

The unit is intended for 12V AC / DC operation only, and must not be connected to the Mains supply or used to switch Mains voltages.

## Operation



N.B. Before programming or setting the clock for the 1st time press the RESET button.

### To set the current TIME and DAY:

1. Hold **CLOCK** and press **DAY** until the correct day is displayed.
2. Hold **CLOCK** and press **HOUR** until the correct hour is displayed.
3. Hold **CLOCK** and press **MIN** until the correct minutes are displayed.

### To set the programs:

1. Press **TIMER** once, 1<sup>on</sup> will appear. This displays the switch on time of the 1st program.
2. Press **DAY** to select the program period. There are 15 settings:  

Mo+Tu+We+Th+Fr+Sa+Su	Mo+We+Fr
Mo, Tu, We, Th, Fr, Sa, or Su	Tu+Th+Sa
Mo+Tu+We+Th+Fr	Mo+Tu+We
Sa+Su	Th+Fr+Sa
Mo+Tu+We+Th+Fr+Sa	
3. Press **HOUR** to select the hour.
4. Press **MIN** to select the minutes.
5. Press **TIMER** once, 1<sup>off</sup> will appear. This displays the switch off time of the 1st program.
6. Repeat steps 2,3 and 4 to set the off day and time.
7. Repeat steps 1 to 6 to set the 2nd, and remaining programs, as necessary.

### Reviewing the programs:

Press **TIMER** each time to toggle through the 8 on and off settings.

### Manual Override

Press **MANUAL** to toggle through ON/AUTO/OFF modes as indicated by the Timer Status Bar.

ON mode turns on the timer.  
OFF mode turns off the timer.  
AUTO mode runs the set program.  
Switching from ON to AUTO will turn ON the timer until the next OFF period.  
Switching from OFF to AUTO will turn OFF the timer until the next ON period.




### Switch status LED indicator

This is a red LED which indicates the switch contact status. Connections 'CO' and 'NO' are closed when the indicator / timer is on.



**12V PROGRAMMABLE  
7 DAY DIGITAL TIMER**

- Daily and weekly programs.
- 8 on/off periods.
- 15 repeat options: day, week, weekend, odd week days, etc.
- Manual Override.
- LCD display with time, weekday, program and switch position.
- Quartz crystal timing with reserve.
- Supply Voltage: 10 - 18V AC / DC
- Consumption: 2VA max.
- Switching Capacity: 10A / 30V DC
- Temperature range: -10EC to 50EC
- Weight: approx. 150g
- Wall mounting.



**MODEL TS2000  
7 DAY TIMER**

**bell system 12V**